

1.DEVO-F12E(white) Control Panel


Mode 2 (Throttle stick on the left)	Left stick	THRO/RUDD stick
	Right stick	ELEV/AILE stick
	Left trim	THRO trim
	Right trim	ELEV trim
Mode 1 (Throttle stick on the right)	Left stick	ELEV/RUDD stick
	Right stick	THRO/AILE stick
	Left trim	ELEV trim
	Right trim	THRO trim

1, 2,4G TX antenna


2.One Key to Start-buzzer control switch

- 3. Retractable Skid Landing Landing Gear Retract Switch and Deploy landing gear
- 4. IOC IOC control switch Inteligent Orientation Control
- 5. Gimbal Roll Gimbal ROLL control
- 6. Left trim
- 7. Left stick
- 8. RUDD trim
- 9. UP kev
- 10. DN key
- 11. EXT key
- 12. 5.8G RX antenna
- 13. ORBIT Round flight mode
- 14. 0 Manual;
 - 1 GPS:
 - 2 Return Home (Flight Mode Switch)
- 15. Start/Stop Video Rec (Camera Start/Stop)
- 16. Gimbal Tilt Gimbal TILT control

switch 2 and 4 on the panel.




- 17. Right stick
- 18. Right trim
- 19. AILE trim
- 20. R key
- 21. L key
- 22. ENT key



2.0 DEVO F12E Radio Setting(White version)

2.1 Boot Screen(Main interface)






2.3 Model Name




Press the UP or DN button to select the stored model number. For example "Model 01", press EXT to return back to the "Model Menu" after finished.



Press UP or DN button to select the characters which need to be changed, press R or L to change the characters. Name model "RUNNER". Press EXT to return to the "Model Menu".

2.4 Wing Type



02 > Model 02

03 >> Model 03

04 >> Model 04 05 ≯ Model 05 06 > Model 06

07 ≯ Model 07 08 >> Model 08


Press R or L to select "Normal", then press EXT to return to the "Model Menu".


-1-

Note: RUNNER 250 match with DEVO-F12E(white) radio, need only use two functions

2.5 Reverse Switch







Press EXT to return back to the "Function Menu" after finished.


2.6 Flail Safe: Start using aircraft Buzzer




Press "UP" or "DN" choose "Flap",press "R" or "L"

choose "Fail Safe", press "UP" or "DN" point to "Failed-Safe Value", press "R" or "L" setting as "U80%". After setting, press "ENT" to confirm and press "EXT" back to "Main Menu".

2.7 Video Setting/OSD information(OSD module should be purchased)





Background:


Press R or L to select Active, Real-time image will be set as background in Main Menu.

Press EXT to switch full screen or half screen to display image and OSD information when in the main interface



Note: The OSD Of Runner 250 just show the data within the green chart.

3.0 Operation Instruction





Note: Please check Runner 250 operation guidence for other details.